



BOSCH

Solution 2000/3000 and B426-M B426-M IP/Ethernet Module setup for RSC+ App Plug & Play Method

1. Login to installer programming on the system and set the Network Module for PNP:
 - On the Icon keypad, this is location 81 – Set value to “3”
 - On the Text keypad (or touchscreen), this is location 7-2-1 - Set value to “3”

Note: This is “Used B4xx-M”
2. Set the panel's module 1 for Cloud Connect at the following locations:
 - On an Icon keypad (or touchscreen), this is location 4456 - Set value to “4”
 - On a Text keypad (or touchscreen), this is location 7-2-1 - Set value to “4”
3. Make sure the B426-M's rotary switch is set to 1 and the jumper is on tamper and connect it via the white 4 pin connector to the system while powered down. Once connected power the system.
4. Download the RSC+ App to your device, being either Android or iOS.
5. Create and register a new account and make sure to complete the email registration to ensure successful login to the account/device.
6. Click on the “+” symbol to add your new IP module and enter a Name for the system, then either manually enter the Cloud ID (the number underneath the QR Code) or click on the QR Scan icon and complete the adding procedure.
7. Once completed press on the site from the list and enter your system pin number to control the system.